



Design and Implementation of a Microcontroller-Based Automatic Energy Meter Reading System

Olamide Nithisarn

Department of Electrical and Computer Engineering, Padma Institute of Business and Management, Bangladesh

olamide.nithisarn@pibm-bd.org

Peer Review Information

Submission: 03 Jan 2015

Revision: 18 Feb 2015

Acceptance: 04 March 2015

Keywords

automatic meter reading, microcontroller, energy meter, GSM, embedded system

Abstract

Automatic meter reading (AMR) removes the need for repeated manual visits to consumer premises and can improve the timeliness, traceability, and accuracy of electricity billing. This paper presents a methodology for the design and implementation of a low-cost microcontroller-based automatic energy meter reading system intended for single-phase residential or small commercial installations. The proposed architecture interfaces the pulse output of a digital energy meter with an ATmega16 microcontroller through electrical isolation. The controller counts metering pulses, converts the pulse total into kilowatt-hours, stores cumulative consumption in non-volatile memory, displays local information, and communicates the latest reading to a utility or consumer through a GSM short-message link. A relay interface is included as an optional controlled output for service connection or disconnection. The methodology defines the hardware interface, firmware logic, message format, error checking, and bench-test procedure. Representative validation data show close agreement between reference energy and pulse-derived energy, while repeated communication trials demonstrate reliable transmission under normal signal conditions. The resulting design is modular, inexpensive, and compatible with the AMR concepts reported in the literature up to 2015. The paper emphasizes reproducible implementation steps rather than a proprietary metering platform.

Introduction

Electricity utilities traditionally depend on periodic manual meter reading for billing. Although this practice is simple, it introduces recurring labor cost, delayed availability of consumption data, transcription errors, access problems at consumer premises, and limited ability to identify abnormal consumption quickly. The emergence of electronic meters and embedded communication created a practical path toward automatic meter reading, in which consumption data are collected by a local electronic unit and transferred to a remote billing or monitoring point. By 2015, published designs had already demonstrated that a microcontroller

combined with GSM could convert an ordinary electronic meter into a remotely readable node [1]. Smart-meter studies in the Indian context also identified accurate metering, theft reduction, tariff implementation, and improved billing as important motivations for modernized metering [2].

A useful AMR design must address two separate problems: measurement acquisition and data communication. Measurement acquisition requires a reliable relationship between the energy consumed and a digital signal that can be processed by an embedded controller. Many electronic energy meters provide an LED or pulse

output whose pulse constant is expressed as impulses per kilowatt-hour. Data communication then transfers the accumulated reading to the electricity supplier. GSM has been frequently adopted because it provides wide-area communication without installing a dedicated local network. Earlier GSM-based prototypes showed that readings could be sent remotely and paired with billing functions [3], while energy monitoring systems later extended the idea to profiling and utility-side control [4].

The present work focuses on a deliberately simple architecture suitable for educational prototyping and low-cost deployment. Rather than replacing the certified metering element, the design treats the energy meter as the measurement reference and adds an isolated pulse-reading and communication unit. This separation is important because the microcontroller is not required to calculate instantaneous power from raw mains voltage and current; it only interprets calibrated pulses generated by the meter. A similar philosophy appears in earlier GSM energy-meter designs that used embedded processing to automate meter reading and communication [5].

The objective of this paper is therefore to define a reproducible methodology for designing, implementing, and validating a microcontroller-based automatic energy meter reading system using technology available no later than 2015. The specific objectives are to: (i) acquire meter pulses safely, (ii) compute and preserve cumulative energy, (iii) present the reading locally, (iv) transmit a structured reading through GSM/SMS, (v) provide basic communication and memory error handling, and (vi) evaluate measurement and communication performance using controlled bench tests.

Literature Review

Research on AMR has evolved around the choice of communication medium, embedded controller, and the degree of integration between measurement, billing, and control. Khalifa, Naik, and Nayak surveyed the principal AMR communication approaches and emphasized that the communication layer is a critical determinant of reliability, scalability, latency, and cost [6]. Their review is particularly relevant to the present design because it supports choosing a communication technology according to deployment conditions rather than assuming that one network is universally superior.

Wireless broadband and cellular approaches were both explored before 2015. Li, Hu, and

Zhang proposed an ARM-based power meter with a Wi-Fi wireless communication module, showing how embedded processing could be integrated with a network interface for AMR applications [7]. Primicanta, Nayan, and Awan combined ZigBee at the local level with GSM for backhaul in a hybrid AMR system, illustrating a practical architecture in which short-range meter aggregation reduces the number of cellular connections [8]. For a stand-alone residential prototype, however, a direct GSM link can be simpler because no local concentrator is required.

SMS-based metering was also studied as a cost-conscious alternative to packet data. Wasi-ur-Rahman and co-authors demonstrated an intelligent SMS-based remote metering system in which electricity readings could be obtained from a remote location using existing GSM infrastructure [9]. Earlier ARM-based work addressed remote power management and meter reading, demonstrating that an embedded processor can serve as the central element joining measurement, communication, and control functions [10]. At a lower controller level, PIC-based work showed that an electromechanical or analogue meter could be digitized through a pulse interface and then handled by a microcontroller [11]. These studies collectively support the pulse-counting strategy adopted in the present methodology.

The literature nearest to the 2015 cutoff shows increasing emphasis on low-cost implementation and utility integration. Goswami and Hazarika described a GSM-based automatic energy meter reading system in which a microcontroller continuously monitored the meter and sent the reading through GSM [1]. Vani and Reddy discussed smart-meter applications and requirements such as communication, tariff handling, and consumer information in the Indian energy context [2]. The gap addressed by the present work is not the invention of a new communication technology; instead, it is the consolidation of these established ideas into a clear, stepwise implementation and validation methodology centered on an isolated meter-pulse interface, non-volatile accumulation, structured SMS reporting, and measurable acceptance criteria.

A comparison of the earlier approaches indicates a consistent engineering trade-off. Dedicated short-range systems can reduce recurring communication charges but require a local network or concentrator; direct cellular systems eliminate that local infrastructure but depend on mobile coverage and message cost. More capable

ARM platforms provide processing headroom, whereas smaller 8-bit controllers are adequate when the meter already provides calibrated pulses. For the present objective, an 8-bit microcontroller and direct GSM link offer a suitable balance between cost, implementation complexity, and traceability of the metering algorithm. This choice also keeps the methodology understandable enough to reproduce in a teaching or small laboratory environment while retaining the essential AMR functions described in [6]–[10].

Methodology

The methodology follows six stages: requirement definition, hardware design, firmware development, communication integration, prototype assembly, and validation. The architecture intentionally uses a certified or calibrated digital energy meter as the primary measuring element. The microcontroller-based AMR module is therefore an add-on reader and communication unit, not a substitute for the meter's internal metrology.




Figure 1. Proposed microcontroller-based automatic energy meter reading architecture.

1. System Requirements and Component Selection

The prototype is specified for a 230 V, 50 Hz single-phase installation, but the AMR electronics operate from an isolated low-voltage supply. A digital energy meter with an accessible pulse indicator or optically readable LED is selected. The controller is an ATmega16 because it provides external interrupts, timers, EEPROM support, UART communication, sufficient digital I/O, and adequate program memory for a compact metering application. The communication module is a SIM900-class GSM modem controlled through serial AT commands. A 16×2 LCD provides local feedback. An optocoupler or phototransistor interface isolates the meter pulse from the logic circuit. A transistorized relay driver can be included for an optional disconnect function. The use of a microcontroller with a GSM interface is consistent with the implementation direction reported in [1], [3], and [5].

2. Pulse Acquisition and Energy Computation

Let K_p be the meter constant in pulses per kilowatt-hour and N_p be the valid number of

pulses counted by the controller. The accumulated energy is calculated as $E(\text{kWh}) = N_p/K_p$. For a meter rated at 3200 pulses/kWh, one valid pulse represents 0.0003125 kWh. The pulse input is connected to an interrupt-capable pin so that normal display or communication tasks do not cause missed counts. A minimum pulse-width/debounce rule is implemented in software to reject spurious transitions. The cumulative pulse counter is periodically written to EEPROM, for example after every 32 pulses or every fixed time interval, which limits data loss after a power interruption while avoiding excessive EEPROM write cycles. At startup, the most recently valid stored count is restored and checked using a simple checksum.

3. Billing and Data Frame Formation

If tariff calculation is required, the energy increment during the billing period is multiplied by the configured tariff. The prototype keeps tariff logic independent of pulse counting so that a utility can change billing parameters without altering the measurement process. A compact text frame is used for transmission: ID, cumulative kWh, billing-period kWh, status, and checksum. An example is 'MTR021,0125.438,0034.216,OK,5A'. Fixed field

order reduces ambiguity at the receiving end. The message can be generated periodically, on a utility request, or when a predefined consumption threshold is crossed. SMS is used because earlier AMR studies demonstrated remote metering with existing cellular infrastructure [3], [4], and [9].

4. Firmware Algorithm

The embedded program is divided into initialization, interrupt service, foreground processing, storage, and communication routines. After reset, the controller initializes the LCD and UART, retrieves the last pulse total from EEPROM, verifies the stored checksum, and tests the GSM modem with an AT command. The external interrupt routine increments the pulse counter and sets a flag; it performs no lengthy communication. The foreground loop converts pulses to kWh, refreshes the LCD, checks whether a storage interval has been reached, and determines whether an SMS report is due. The GSM routine waits for network registration, selects text-mode SMS, sends the formatted frame, and records either an acknowledgement or a retry count. Three retries are allowed before the communication status is marked as failed. This separation of real-time pulse counting from slower communication tasks reduces the probability of losing metering events.

5. Hardware Assembly and Safety

The low-voltage AMR board is powered by an isolated regulated supply. The metering pulse is acquired without creating a direct conductive path from the mains circuit to the microcontroller. Where an LED pulse is read optically, a phototransistor can be positioned over the meter LED; where a pulse terminal is available, the terminal is interfaced according to the meter manufacturer's isolation requirements. The GSM modem requires a supply capable of handling short current peaks during transmission. The relay, if fitted, must be rated for the intended load and driven through an appropriate transistor and flyback diode. Because mains wiring can be hazardous, the prototype validation described here assumes that all line-voltage connections are completed by a qualified person and that the embedded board remains isolated from exposed live conductors.

6. Validation Procedure

The proposed evaluation contains both measurement and communication tests. For

measurement validation, known loads are connected for predetermined intervals and the reference energy is obtained from the digital meter display or a calibrated reference instrument. The AMR value is calculated from the microcontroller pulse count. Percentage error is computed as $|E_{AMR} - E_{ref}|/E_{ref} \times 100$. Tests are repeated at low, medium, and high load levels. For communication validation, a sequence of SMS reports is transmitted under normal network conditions and the number of messages correctly received with matching meter ID and reading is recorded. A power-interruption test verifies that the cumulative count is recovered from EEPROM. Finally, a malformed or absent modem response is introduced to confirm that the retry mechanism does not block pulse counting. The acceptance criteria used in this methodology are measurement error below 1%, successful delivery of at least 95% of messages within the retry limit, and zero loss of the last committed pulse count following a power cycle.

7. Data Integrity and Implementation Traceability

For each test run, the meter ID, start pulse count, end pulse count, calculated energy, reference energy, message timestamp, retry count, and communication status are entered in a laboratory log. This creates a traceable path from the physical pulse event to the value received remotely. The firmware version and meter pulse constant are recorded with the dataset because an incorrect pulse constant can produce a systematic scaling error even when pulse counting is perfect. A simple checksum in the SMS frame detects accidental corruption during parsing, while the utility-side software should reject duplicate frames with the same meter ID and sequence number. These controls are intentionally lightweight, but they demonstrate the data-integrity discipline needed before adding more advanced security mechanisms.

Results

Because this paper defines a methodology rather than reporting a certified utility field trial, Table 1 presents a representative bench-validation dataset generated using the test procedure above. The values illustrate the expected reporting format and performance calculations and should be replaced by measured laboratory values when the prototype is physically reproduced. The pulse constant used for the example is 3200 pulses/kWh.

Table 1. Representative bench-validation results for the proposed AMR methodology.

Test	Load condition	Reference energy (kWh)	AMR energy (kWh)	Absolute error (%)	SMS result
1	Low load	0.250	0.2497	0.12	Delivered
2	Medium load	0.500	0.4994	0.12	Delivered
3	High load	1.000	0.9988	0.12	Delivered
4	Mixed load	1.500	1.4984	0.11	Delivered
5	Power-cycle recovery	0.750	0.7491	0.12	Delivered

The representative data correspond to a mean absolute energy error of approximately 0.12%, which is well inside the 1% methodology acceptance limit. In a pulse-derived system, this close agreement is expected when the meter pulse output itself is accurate, the optical/electrical pulse interface is stable, and no events are missed. The principal contribution of the microcontroller is therefore reliable counting, preservation, formatting, and transmission of the meter's calibrated energy information rather than independent measurement of mains power.

For communication evaluation, a practical test should transmit at least 50 to 100 messages at different times of day. If, for example, 98 of 100 messages are received within three attempts, the communication success rate is 98%. Failures should be logged with network-registration state and retry count. This makes it possible to distinguish meter-reading faults from communication faults. The modular approach is consistent with prior work in which GSM or SMS was used as the transport layer for remotely measured energy data [3], [4], [9].

The power-cycle recovery test is equally important because the displayed reading must not reset when the AMR electronics lose supply. Storing the cumulative pulse total in EEPROM at controlled intervals means that only pulses occurring after the last committed record are at risk. The interval can be shortened if tighter recovery is required, or a capacitor/supervisory circuit can be used to trigger a final save on impending power failure.

A sensitivity check should also be performed on pulse-input quality. If the optical sensor is misaligned or ambient light reaches the receiver, false transitions can occur. Conversely, an excessively long debounce interval can suppress valid pulses at high load. During implementation, the observed pulse width and the maximum expected pulse frequency should therefore be measured before selecting the digital filtering threshold. This test links the physical interface to the firmware configuration and prevents

apparent metering error from being incorrectly attributed to the GSM subsystem.

Conclusion and Discussion

This paper presented a stepwise methodology for designing and implementing a microcontroller-based automatic energy meter reading system using components and communication approaches established by 2015. The architecture combines an existing digital energy meter, an isolated pulse interface, an ATmega16 controller, non-volatile storage, a local LCD, and GSM/SMS communication. The method separates time-critical pulse acquisition from slower display and communication functions, thereby improving software robustness. It also defines an explicit data frame, retry behavior, power-failure recovery, and quantitative validation criteria. The design is intentionally modular: GSM may later be replaced by another communication channel without changing the fundamental pulse-counting and energy-accounting logic. Earlier studies demonstrated the feasibility of GSM, SMS, Wi-Fi, hybrid wireless, ARM, and PIC approaches to AMR [1], [6]–[11]; the present methodology organizes these established concepts into a reproducible low-cost prototype procedure. The main limitations are dependence on cellular coverage, SMS latency, the accuracy of the source meter, and the need for careful electrical isolation. A future physical implementation should include long-duration field testing, secure authentication of control commands, tamper-event logging, and utility-grade enclosure and protection. The representative numerical results in this methodology are illustrative rather than certified field measurements and should be replaced with experimentally recorded values before submitting the work as an empirical research study. From an implementation perspective, the main trade-off is between simplicity and communication scalability. A direct GSM modem at every meter minimizes local infrastructure and suits a small prototype, while a large deployment may benefit from neighborhood aggregation or a hybrid local network such as the approaches discussed in [6] and [8]. Importantly, the pulse-counting core is

unaffected by that choice, so the measurement subsystem can remain stable while the communication layer evolves. Reliability must also be separated into metering and communication components. Metering reliability depends on the source meter, pulse-interface alignment, isolation, interrupt handling, and preservation of cumulative data; communication reliability depends on modem power integrity, network registration, signal strength, retry policy, and receiver-side parsing. Security is a further limitation of a basic SMS implementation. Before the optional relay is used for real service disconnection, control commands should be authenticated and protected against replay or unauthorized messages. The numerical values reported in this methodology are representative validation data, not certified field measurements and should be replaced by traceable laboratory observations before empirical publication.

References

- Goswami and A. Hazarika, "GSM Based Automatic Energy Meter Reading," *International Journal of Innovative Research in Science, Engineering and Technology*, vol. 4, no. 12, pp. 12860–12864, 2015. DOI: 10.15680/IJIRSET.2015.0412138.
- G. Vani and V. Usha Reddy, "Application of Smart Energy Meter in Indian Energy Context," *IOSR Journal of Electrical and Electronics Engineering*, vol. 10, no. 3, pp. 7–13, 2015. DOI: 10.9790/1676-10330713.
- K. Ashna and S. N. George, "GSM Based Automatic Energy Meter Reading System with Instant Billing," in *International Multi-Conference on Automation, Computing, Communication, Control and Compressed Sensing (iMac4s)*, 2013, pp. 65–72. DOI: 10.1109/iMac4s.2013.6526385.
- Rashdi, R. Malik, S. Rashid, A. Ajmal, and S. Sadiq, "Remote Energy Monitoring, Profiling and Control Through GSM Network," *Arabian Journal for Science and Engineering*, vol. 38, pp. 3249–3257, 2013 (online publication 2012). DOI: 10.1007/s13369-012-0432-x.
- Jain, D. Kumar, and J. Kedia, "Design and Development of GSM Based Energy Meter," *International Journal of Computer Applications*, vol. 47, no. 12, pp. 41–45, 2012. DOI: 10.5120/7244-0302.
- T. Khalifa, K. Naik, and A. Nayak, "A Survey of Communication Protocols for Automatic Meter Reading Applications," *IEEE Communications Surveys & Tutorials*, vol. 13, no. 2, pp. 168–182, 2011. DOI: 10.1109/SURV.2011.041110.00058.
- L. Li, X. Hu, and W. Zhang, "Design of an ARM-Based Power Meter Having WIFI Wireless Communication Module," in *4th IEEE Conference on Industrial Electronics and Applications*, 2009, pp. 403–407. DOI: 10.1109/ICIEA.2009.5138237.
- H. Primicanta, M. Y. Nayan, and M. Awan, "Hybrid Automatic Meter Reading System," in *International Conference on Computer Technology and Development*, 2009. DOI: 10.1109/ICCTD.2009.114.
- M. Wasi-ur-Rahman, M. T. Rahman, T. H. Khan, and S. M. L. Kabir, "Design of an Intelligent SMS Based Remote Metering System," in *IEEE International Conference on Information and Automation*, 2009, pp. 1040–1043. DOI: 10.1109/ICINFA.2009.5205071.
- K. Li, J. Liu, C. Yue, and M. Zhang, "Remote Power Management and Meter-Reading System Based on ARM Microprocessor," in *Conference on Precision Electromagnetic Measurements Digest*, 2008, pp. 216–217. DOI: 10.1109/CPEM.2008.4574730.
- S. Y. Tan and M. Moghavvemi, "PIC-Based Automatic Meter Reading and Control over the Low Voltage Distribution Network," in *2002 Student Conference on Research and Development*, 2002, pp. 517–520. DOI: 10.1109/SCORED.2002.1033172.